

# **Demolition Breaker XGT®**

## **HM004G**

80V • 72.8J • 28.6mm • 870 min?<sup>1</sup>

#### HM004G 80Vmax (40Vx2) XGT Brushless Hex Demolition Breaker

With the combination of the XGT system and a high-output brushless motor, HM004G offers a remarkable 72.8J impact energy that is equivalent to our corded models. In addition, HM004G achieves an increased work efficiency and a lower vibration level due to its anti vibration housing structure. HM004G is equipped with numerous features including Constant Speed Control, Soft Start, Soft No Load, Anti-Vibration Technology (AVT), Auto-Start Wireless System (AWS), Extreme Protection Technology (XPT), Maintenance Warning function, Power On/Off function, and Twin LED job lights.



### **SPECIFICATIONS**

Impact Energy (EPTA)
Impacts per Minute (IPM)
Sound Pressure Level

Sound Power Level (LWA)
Vibration Uncertainty (K Factor)

Vibration: Chiselling

Noise Uncertainty (K Factor)

Brushless Motor AWS FUNCTION Adapted for Hex Shank

Product Dimensions (L x W x H): Tool weight without battery (EPTA)

**Battery Voltage** 

72,8 J 870 min?<sup>1</sup> 95 dB(A) 103 dB(A) 1,5 m/s<sup>2</sup> 6,5 m/s<sup>2</sup> 1.62 dB(A) YES YES 28.6mm

882 x 227 x 540 mm

28.3 kg 2 x 40 V MAX

#### **USER BENEFITS**

- Â Powered by two 40VMAX XGT Lithium-ion batteries to provide 80V MAX volts
- Â High impact energy 72.8J achieved with combination of XGT system with high power brushless motor
- Low vibration 6.5m/s² Anti Vibration Housing, Active Dynamic Vibration absorber, Counter Weight Mechanism keeps the vibration lower
- Â Power on/off function prevents accidental startup when the trigger is pressed
- Â Auto power OFF function automatically switches off the power of the hammer, 5 minutes after the trigger switch is released to save battery life and also for operator safety
- A Low battery Warning indication (blinking RED)
- Â Maintenance Warning Function: When the tool's cumulative operating time exceeds 45 hours, the maintenance indicator lamp blinks red, indicating for maintenance.
- Â Dust Extraction Capability with optional Makita Dust Attachment Kit and also featured AWS technology for wireless power-on/off communication between tool and dust extractor
- Â Soft no load function automatically reduces the speed of the motor when idling to help increase tool life and performance
- Â Constant Speed Control maintain same speed even under load
- Â Soft Start: Breaker starts smoothly then rapidly accelerates to maximum speed to reduce the initial start-up shock
- Â Job Light with TWIN LEDs With preglow and afterglow functions for dark jobsites
- Â eXtreme Protection Technology: Dust and water resistance for operation in harsh conditions
- Â Dust Extractor Attachment Set: 197168-2 (without hose) / 197148-8 (with hose)

Link to Product page - https://makitauae.com/product/hm004g-demolition-breaker-xgt/

Disclaimer: Information contained in this leaflet are UAE specific and to be used only as a guide