



Combination Hammer

HR2661

800 W • SDS-Plus • 26 mm • 2,9 J

Three-mode, anti-vibration rotary hammer with dust bag and quick-change chuck for professional use

A robust combination hammer for SDS-Plus bits with an AVT anti-vibration system and HEPA self dust collection. Suitable for impact and unstressed drilling and chipping. 800 W output and speed can be adjusted between 0 and 1 200 min⁻¹ from a switch. Impact energy of 2,9J and optimal drilling range of 8 – 18 mm in concrete, with a max. capacity of 26 mm.



TECHNICAL

SPECIFICATIONS

| | |
|---|-------------------------|
| MAXIMUM OUTPUT POWER | HR2661 |
| NO LOAD SPEED | 800W |
| IMPACT | 0-1100min ⁻¹ |
| MAX. DRILLING DIAMETER IN WOOD | 0-4500min ⁻¹ |
| MAX. DRILLING DIAMETER IN CONCRETE | 32mm |
| MAX. DRILLING DIAMETER IN STEEL | 26mm |
| OPTIMUM DRILLING DIAMETER RANGE IN CONCRETE | 13mm |
| IMPACT ENERGY | 8-18mm |
| DRILLING DIAMETER WITH TCT CORE BIT | 2,2J |
| ADAPTED FOR SDS-PLUS BITS | 68-80mm |
| POWER SUPPLY CORD | Yes |
| PLASTIC CARRYING CASE | 2,5m |
| SOUND POWER LEVEL (LWA) | Yes |
| SOUND PRESSURE LEVEL (LPA) | 101dB(A) |
| NOISE UNCERTAINTY (K FACTOR) | 90dB(A) |
| VIBRATION LEVEL (3 AXES), DRILLING | 3dB(A) |
| VIBRATION LEVEL (3 AXES), IMPACT DRILLING | ?2,5m/s ² |
| VIBRATION: CHISELLING | 9,5m/s ² |
| VIBRATION UNCERTAINTY (K FACTOR) | 6,0m/s ² |
| PRODUCT WEIGHT | 1,5m/s ² |
| PRODUCT DIMENSIONS (L X W X H): | 3,3-4,4kg |
| EAN | 666x89x228mm |
| | 88381845991 |

USER BENEFITS

- 3-Mode operation for "Rotation Only", "Hammering with Rotation" or "Hammering Only" for multiple applications
- AVT (Anti-Vibration Technology) ensures extra-low vibration performance
- Depth gauge for increased drilling consistency
- Double insulated
- HEPA filter removes particles with an efficiency rating of 99.75%
- Rear handle with soft rubber grip, ergonomically designed for comfortable operation
- Variable speed trigger allows operator to adjust speed based on materials or application

Link to Product page - <https://makitauae.com/product/hr2661-combination-hammer/>